

Red Locomotive LED Marker Light

RH-PAR60-2R-LED

- ▶ Our LED replacement uses 4.8W opposed to 60W
- ▶ This is a replacement for the typical PAR60/2R

**3 YEAR
WARRANTY**

Optical Features

- ▶ Color - Red
- ▶ LED Wavelength - 660 nm
- ▶ Light Intensity - exceeds 100 Candela Industry Standard
- ▶ Color Options: White, Yellow, Blue, Green
- ▶ Minimum 100 Candela output throughout the entire Voltage Range
- ▶ Light Direction - Front

Electrical Features

- ▶ Operating Voltage Range - 10 to 95 VDC
- ▶ Voltage Protection
 - Breakdown Voltage - VBD 120 VDC
 - Surge Current (IRMS) - 9.1ARMS
 - Peak Power - 1500W
- ▶ Inverse Voltage Protection - Non-Polarized
- ▶ Connection - As per Customer Requirement

Specifications

Operating Voltage	10-80VDC
Rated Life	50,000 hours
Power Consumption	4.8W
Measurements	Typical PAR46 measurements
LED Quantity	72
Base	Screw Terminal
Size	3"x 6"
Warranty	3 years



Railhead Corp.
224 Shore Court, Burr Ridge, IL 60527
800-235-1782 708-844-5500
www.railheadcorp.com